

112900 to 112999**SERVICE ENGINE****SALES MANUAL**
**MODEL 112900 SERIES ENGINES REPLACED WITH
STANDARD SERVICE ENGINES**

In most cases, the Original Type numbers shown may be replaced by a Service Type Number without making any changes. Necessary changes of engine parts such as crankshafts, reduction parts, blower housings, etc., are noted. Other differences, such as mufflers, elbows, deflectors, etc., are not listed but are very important for safety and engine performance. Be sure the exhaust system on the replacement engine duplicates the system originally selected by the equipment manufacturer. Parts that are suitable for additional use should be transferred. Before making any conversion, check the data shown in the column labeled "REMOVE, ADD and NOTE." See if the changes, which are shown, are actually necessary on the application in question. Often a standard service engine will be a WORKABLE replacement without converting to such things as a special fuel tank or starter position.

If the crankshaft number does not appear in the "Original Engine" column, consult the Illustrated Parts List for the correct service replacement crankshaft number.

Engine Replacement Notes:
Short Block Notes:

The SHORT BLOCK part number shown, is the assembly which can be used to rebuild the Original Type Number. If a letter appears after the short block number, it indicates the short block must be modified. The change denoted by each letter is as follows:

112900 to 112999

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
3130	112902	492087	10M902	0016							All	3100	398220	
3131	112902	492094	10M902	0018							All	3000		
3133	112902	492087	10M902	0016							All	3000		
3134	112982	492096	No Replacement Repair With Individual Parts.								All	3100		
3911	112902	492096	10M902	0015							All	3100		
3912	112982	492096	No Replacement Repair With Individual Parts.								All	3500		
3913	112982	492096	No Replacement Repair With Individual Parts.								All	3100		