

326400 to 326499

SERVICE ENGINE



SALES MANUAL

**MODEL 326400 SERIES ENGINES REPLACED WITH
 STANDARD SERVICE ENGINES**

In most cases, the Original Type numbers shown may be replaced by a Service Type Number without making any changes. Necessary changes of engine parts such as crankshafts, reduction parts, blower housings, etc., are noted. Other differences, such as mufflers, elbows, deflectors, etc., are not listed but are very important for safety and engine performance. Be sure the exhaust system on the replacement engine duplicates the system originally selected by the equipment manufacturer. Parts that are suitable for additional use should be transferred. Before making any conversion, check the data shown in the column labeled "REMOVE, ADD and NOTE." See if the changes, which are shown, are actually necessary on the application in question. Often a standard service engine will be a WORKABLE replacement without converting to such things as a special fuel tank or starter position.

If the crankshaft number does not appear in the "Original Engine" column, consult the Illustrated Parts List for the correct service replacement crankshaft number.

Engine Replacement Notes:

- NOTE 39:** Original engine used special PTO Shaft Extension on Flywheel side. Transfer Shaft Extension #230950, Screen #222044 and Fan/Pulley #211739 from original engine, or add as new parts.
- NOTE 42:** Original engine was equipped special Remote Throttle Control or Governor Control. Transfer these parts to replacement engine.
- NOTE 49:** Replacement engine is equipped with Electric Starter. However, if original Electric Starter parts are suitable for additional service, the parts can be transferred to Rope Starter Model 326431 Type 2520.
- NOTE 50:** Replacement engine is not available in the U. S. A. Repair with individual parts.
- NOTE 53:** Reverse Engine Base.
- NOTE 58:** The original engine was equipped for or with a 12 Volt Starter Generator. Transfer Starter parts to replacement engine.
- NOTE 65:** Transfer base from original engine, or add 391165 base as a new part.
- NOTE 77:** Transfer Fuel Pump and related parts from original engine to replacement engine.
- NOTE 78:** Transfer Fuel Tank Assembly from the original engine to the replacement engine.
- NOTE 84:** Transfer Intake Elbow and Governor Link from original engine, or add #211419 Intake Elbow and #26725 Governor Link.
- NOTE 86:** Transfer Lever Stop Switch and/or Ground Wire Terminal to replacement engine.
- NOTE 88:** Transfer Muffler and/or Spark Arrester Assembly from the original engine if suitable for additional service or add new parts as required
- NOTE 93:** Transfer Starter Panel group and/or Starter Motor to replacement engine.

Short Block Notes:

The SHORT BLOCK part number shown, is the assembly which can be used to rebuild the Original Type Number. If a letter appears after the short block number, it indicates the short block must be modified. The change denoted by each letter is as follows:

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
0020	326431	261218	326431	2520					50		01	3750	393870	
											02	3750		
0021	326431	261219	No Replacement Repair With Individual Parts.									01	2900	
											02	2900		
0022	326431	261245	No Replacement Repair With Individual Parts.									01	3700	
											02	3700		
0023	326434	261218	326437	2528					50		ALL	3750	393870	
0027	326437	261218	326437	2527					50		ALL	3750	393870	
0028	326437	261218	326437	2528					50		ALL	3750	393870	
0050	326431	261223	326431	2550					50		ALL	3750		
0060	326432	261228	326432	2561	1	261413	1	261228	50	2560	01	3750		
0061	326432	261413	326432	2561					50		01	3750		
0062	326432	261407	No Replacement Repair With Individual Parts.									ALL	3700	
0063	326437	261245	326437	2563					50		All	3700		
0111	326431	261218	326431	2520					50		All	2900	393870	
0112	326431	261219	326431	2520	1	261218	1	261219	50	0656	01	2900		
						1	299609	1	291675			02	3600	
											03	2900		

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
0113	326431	261225	326431	2520	1	261218	1	261225	50		01	2900		
					1	299609	1	291675						
0114	326431	261245	326431	2520	1	261218	1	261245	50		01	2900		
					1	299609	1	291675						
0115	326437	261218	326437	2527					50		ALL	2900	393870	
0116	326431	261223	326431	2550					50		All	2900		
0117	326431	261218	326431	2520					50		All	2900	393870	
0118	326434	261218	326437	2527					50		01	2900	393870	
0119	326432	261228	326432	2561					50		01	2900		
0120	326431	261218	326431	2520					50		01	2900	393870	
									65					
0121	326431	261218	326431	2520	1	391065	1	22963	50		01	2900	393870	
								1 391068	65					
									77					
0123	326437	261218	326437	2527					50		01	2900	393870	
									65		02	2650		
0124	326432	261413	326432	2561					50		01	2900		
0126	326435	261218	326437	2527					50		01	3400	393870	
									53					
									65					
0127	326431	261220	326431	2582					50		ALL	3600		
0128	326431	261219	326431	2520	1	261218	1	261219	50		01	2900		
					1	391062	1	291710			02	3300		
											03	2900		
											04	2900		
											05	2900		
											09	2900		
0129	326431	261245	326431	2520	1	261218	1	261245	50		01	2900		
					1	391062	1	291710						
0130	326431	261223	326431	2550					50		01	2900		
0131	326431	261218	326431	2520				1 221976	50		02	2900	393870	
								1 299907						
0132	326431	261218	326431	2520	1	298975	1	391116	50		All	3800	393870	
0133	326431	261220	326431	2582					50		All	3750		
0134	326434	261218	326437	2527	1	391065	1	391070	50		All	3400	393870	
0135	326437	261218	326437	2527	1	391065	1	22963	50		All	3400	393870	
								1 391070						
0136	326431	261221	326431	2520	1	261218	1	261221	39		01	3500		
					1	391065	1	391070	42					
								1 93722	50					
									58					
									65					
0137	326431	261218	326431	2520					50		01	3600	393870	
0138	326431	261218	326431	2520				1 298926	50		01	2900	393870	
0139	326431	261222	326431	2520	1	261218	1	261222	39		01	3500		
					1	391065	1	391070	42					
								1 93722	50					
									58					
0140	326434	261218	326437	2528	1	391065	1	391070	39		01	3750	393870	
									49					
									50					
									65					
0141	326431	261218	326431	2520					50		01	2900	393870	
											02	3200		
											03	2900		
											04	2900		

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block		
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes	
0142	326431	261218	326431	2520					50 53		01	2900	393870		
0143	326437	261223	326437	2527	1	261218	1	261223	50		01	2900			
					1	299609	1	291675							
0144	326431	261218	No Replacement Repair With Individual Parts.									All	3600	393870	
0145	326434	261218	326437	2528					49 50		01	3600	393870		
0146	326431	261218	326431	2520					50		01	3750	393870		
0147	326431	261223	326431	2550	1	298809	1	29693	50		01	3100			
0148	326437	261218	326437	2527					39 50		01	2900	393870		
0149	326437	261223	326437	2527	1	261218	1	22963	50		01	3200			
					1	299609	1	261223	65						
					1	391065	1	291675							
								1	391070						
0150	326434	261223	326431	2550					50 58		01	2500			
0151	326434	261223	326431	2550					50 58		01 02	2900 2900			
0152	326434	261218	326437	2528					39 49 50		01	2900	393870		
0153	326431	261245	326431	2520	1	261218	1	261245	50		01	3700			
					1	299609	1	291675							
0154	326431	261218	326431	2520				1	299361	50	01	3600	393870		
0155	326434	261218	326437	2528				1	299361	49 50	01	3600	393870		
0156	326431	261223	326431	2550					50		01	3100			
0157	326431	261218	326431	2520	1	391065	1	391068	50 53 65 77		01	3600	393870		
0158	326431	261218	326431	2520	1	391065	1	391068	50 53 65 77		01	3600	393870		
0159	326434	261218	326437	2528					49 50		01 02	2900 2900			
0160	326432	261255	326432	2561	1	261413	1	261407	50		01	3700			
					1	299609	1	291675							
0161	326431	261218	326431	2520					50		01	2900	393870		
0162	326437	261218	326437	2527	1	391065	1	391070	50 53 65		01	3600	393870		
0163	326437	261218	326437	2527	1	391065	1	391070	39 50 65		01	3600	393870		
0164	326437	261218	326437	2527	1	391065	1	391068	50 53 65 77		01 02	3300 3300	393870		
0165	326437	261218	326437	2527	1	391065	1	391068	50 53 65 77		01	3600	393870		
0166	326431	261218	326431	2520	1	391065	1	391070	50 53		01	2900	393870		

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
0167	326437	261223	326437	2527	1	261218	1	261223	50		01	3600		
					1	299609	1	291675						
0168	326437	261218	326437	2527			1	299361	50		01	3600	393870	
0169	326431	261218	326431	2520	1	22963	1	391068	39		01	3600		
					1	391065	1	93583	50					
					1	92674			53					
									58					
									65					
									77					
0170	326437	261223	326437	2527	1	261218	1	261223	50		01	3600		
					1	391062	1	291710	53		02	3600		
					1	391065	1	391068	65					
									77					
0171	326437	261225	326437	2527	1	261218	1	261225	50		01	2900		
					1	299609	1	291675						
0172	326437	261223	326437	2527	1	261218	1	261223	50		01	2800		
					1	299609	1	291675	53					
					1	391065	1	391070	65					
0173	326431	261223	326431	2550	1	391065	1	391070	50		01	2800		
									53					
									65					
0174	326437	261223	326437	2527	1	261218	1	261223	50		01	2500		
					1	299609	1	291675	53					
									65					
0175	326434	261245	326437	2528	1	261218	1	261245	49		01	3600		
					1	299609	1	291675	50					
0176	326431	261245	326431	2520	1	261218	1	261245	50	0674	All	3600		
					1	299609	1	291675						
0177	326431	261218	326431	2520					50		01	3600	393870	
0178	326437	261218	326437	2527					50		01	2650	393870	
									65					
0179	326431	261218	326431	2520					50		01	2900	393870	
									65					
0180	326437	261218	326437	2527	1	391065	1	391070	50		01	3600	393870	
									53					
									65					
0181	326431	261219	326437	2528	1	261218	1	261219	49		01	3650		
					1	391062	1	291710	50					
					1	92674	1	93583						
0182	326437	261218	326437	2527	1	221851	1	222283	50		01	3200	393870	
					1	391065	1	392035	65					
									77					
0183	326431	261245	326431	2520	1	261218	1	261245	50		01	3750		
					1	299609	1	291675	65					
0184	326437	261218	326437	2527	1	391065	1	22963	39		01	3600	393870	
					1	92674	1	391068	50					
								1	93583					
									53					
									65					
									77					
0185	326437	261223	326437	2527	1	220197	1	261223	50		01	2800		
					1	261218	1	291675	53		02	2800		
					1	299609	1	391070	65					
					1	391065								
0186	326431	261223	326431	2550	1	391065	1	391070	50		01	2800		
									53					
									65					

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
0187	326431	261218	326431	2520	1	298975	1	391116	50 53		01	3800	393870	
0188	326437	261223	326437	2527	1	261218	1	261223	50		01	3600		
					1	299609	1	291675						
0189	326437	261219	326437	2527	1	261218	1	261219	50	0668	01	3750		
					1	391062	1	291710						
0190	326431	261220	326431	2582					50		01	3600		
0191	326434	261218	326437	2528					49 50		01	3750	393870	
0192	326437	261223	326437	2527	1	261218	1	261223	42		01	3600		
					1	299609	1	291675	50					
					1	391065	1	391068	53 65 77					
0193	326437	261223	326437	2527	1	261218	1	261223	50		01	2900		
					1	299609	1	291675						
0194	326431	261218	326431	2520	1	298975	1	391116	50		01	2900	393870	
0195	326431	261218	326431	2520	1	298975	1	261322	50		01	3800	393870	
								298926	53					
								391116						
								392150						
0196	326431	261225	326431	2520	1	261218	1	261225	50		01	3750		
					1	299609	1	291675						
0197	326432	261255	326432	2561	1	261413	1	261407	50		01	1850		
					1	299609	1	291675						
0198	326435	261245	326437	2527	1	261218	1	261245	50		01	3600		
					1	299609	1	291675	53					
					1	391065	1	392235	65					
					1	92674	1	93583	77					
0199	326434	261218	326437	2528	1	295924	1	296180	39 49 50		01	2900	393870	
0200	326431	261218	326431	2520				293739	50		01	2900	393870	
0201	326437	261218	326437	2527	1	391065	1	391070	50 53 65		01 02	3800 3600	393870	
0202	326431	261218	326431	2520	1	298975	1	221976	50		ALL	3600	393870	
								261322	53					
								299907						
								391116						
								392150						
0203	326431	261219	326431	2520	1	261218	1	261219	50		01	3650		
					1	391062	1	291710						
0204	326431	261222	326431	2520	1	261218	1	261222	39		01	3500		
					1	391065	1	391070	42 50 58 65					
0205	326431	261245	326431	2520	1	211981	1	211889	50		01	3750		
					1	222357	1	221953	65					
					1	261218	1	261245						
					1	299609	1	291675						
0206	326434	261218	326437	2528	1	391065	1	391070	49 50		01	2900		
0207	326431	261218	326431	2520					50		01	3000	393870	

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
0208	326434	261223	326437	2528	1	261218	1	261223	49		01	3600		
					1	299609	1	291675	50					
0209	326437	261219	326437	2527	1	261218	1	261219	50		01	2900		
					1	299609	1	291675						
0210	326437	261302	326437	0630					50		01	3300		
0211	326437	261218	326437	2527	1	391065	1	391070	50		01	3000	393870	
0212	326434	261218	326437	2528	1	391065	1	391070	49		01	3600	393870	
									50					
0213	326437	261218	326437	2527	1	391065	1	391070	50		01	3000	393870	
					1	391520	1	392602	78					
0214	326431	261218	326431	2520					50		01	3600	393870	
0215	326437	261218	326437	2527					50		01	3600	393870	
									53					
									65					
0216	326432	261255	326432	2561	1	261413	1	261407	50		01	3800		
					1	299609	1	291675						
					1	92674	1	93583						
0217	326435	261245	326437	2563					50		01	3800		
0218	326434	261218	326437	2528					49		01	2900	393870	
									50					
0219	326434	261223	326437	2528	1	261218	1	261223	50		01	2900		
					1	299609	1	291675						
0220	326431	261218	326431	2520	1	298975	1	261322	50		01	3800	393870	
									53					
0221	326435	261218	326437	2527					50		01	3700	393870	
0222	326437	261408	326437	2527	1	261218	1	22963	50		01	3500		
					1	391065	1	261408	77					
					1	92674	1	392035						
0223	326432	261228	326432	2561					50		01	3600		
									65					
0224	326437	261245	326437	2563					50		01	3600		
0225	326431	261218	326431	2520					50		01	3600	393870	
0226	326434	261218	326437	2528	1	391065	1	391070	50		01	3600	393870	
0227	326434	261218	326437	2528	1	220197	1	261137	39		01	3750	393870	
									42					
									50					
									65					
									78					
0228	326431	261222	326431	2520	1	261218	1	261222	39	0678	01	3500		
					1	391065	1	391070	42					
									50					
									58					
									65					
0229	326437	261218	326437	2527	1	391065	1	391070	50		01	3600	393870	
									78					
0230	326435	261218	326437	2527					50		01	3200	393870	
									65					
0231	326437	261223	326437	2527	1	261218	1	261223	50		01	3750		
					1	391062	1	291710						
0232	326431	261218	326431	2520	1	298975	1	29693	50		01	3800	393870	

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
0233	326431	261245	326431	2520	1	261218	1	261245	50		01	3800		
					1	299609	1	291675	53					
0234	326435	261218	326437	2527	1	391065	1	392235	42	0705	01	2800		
									50					
									53					
									65					
									77					
0235	326435	261245	326437	2563	1	391065	1	392235	50		01	3600		
					1	92674	1	93583	65					
									77					
0236	326437	261245	326437	2563	1	220197			50		01	3750		
0237	326432	261255	326432	2561	1	261413	1	261407	50		01	3600		
					1	391062	1	291675						
					1	92674	1	291710						
								1	93583					
0238	326437	261245	326437	2563	1	391062	1	291710	50		01	3750		
					1	92674	1	298926						
								1	93583					
0239	326431	261218	326431	2520	1	298975	1	391116	50		01	3800	393870	
								1	392150		02	3800		
0240	326437	261218	326437	2527	1	391065	1	391068	50		01	3300	393870	
									53					
									65					
									77					
0241	326432	261407	326432	2561	1	261413	1	261407	50		01	3750		
					1	299609	1	291675						
0242	326432	261407	326432	2561	1	261413	1	261407	50	0723	01	1850		
					1	299609	1	291675						
0243	326432	261407	326432	2561	1	261413	1	261407	50		01	3750		
					1	391062	1	291710						
					1	92674	1	93583						
0244	326432	261407	326432	2561	1	261413	1	261407	50		01	3800		
					1	299609	1	291675						
					1	92674	1	93583						
0245	326431	261218	326431	2520					50		01	2900	393870	
									65					
0246	326432	261355	326432	2561	1	261413	1	261407	50		01	3600		
					1	299609	1	291675	65					
0247	326431	261245	326431	2520	1	261218	1	261245	50		01	3750		
					1	299609	1	291675						
0248	326437	261223	326437	2527	1	261218	1	260584	50		01	3600		
					1	391062	1	261223	53					
					1	391065	1	291710	65					
								1	392235					
									84					
0249	326437	261218	326437	2527	1	220197	1	391070	50		01	3600	393870	
					1	391065								
0250	326437	261218	326437	2527					50		01	3450	393870	
0251	326437	261218	326437	2527	1	391065	1	391070	50		01	3000	393870	
								1	66538					
0252	326437	261220	326437	2527	1	220197	1	222283	50		01	3600		
					1	221851	1	261220	65					
					1	22963	1	66538						
					1	261218	1	93583						
0253	326432	261413	326432	2561					50		01	3750		
									65					

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
0254	326431	261219	326431	2520	1	22963	1	261219	50		01	3650		
						1	261218	1	291710	58				
						1	391062	1	93583	65				
						1	92674							
0255	326431	261245	326431	2550	1	211981	1	222669	50		01	3750		
						1	222357	1	222670	65				
						1	22963	1	261245					
						1	261223	1	93843					
						1	91203							
						1	92674							
0256	326431	261219	326431	2550	1	261223	1	261219	50	0656	All	3600		
0257	326437	261223	326437	2527	1	220197	1	261223	50	0721	01	2900		
						1	261218	1	291675					
						1	299609							
0258	326431	261219	326431	2520	1	261218	1	261219	50	0668	01	3750		
						1	391062	1	291710					
0259	326431	261476	326431	2520	1	261218	1	261476	50	0647	01	3650		
						1	391062	1	291710	65				
						1	92674	1	93583					
0260	326432	261407	326432	0061	1	261413	1	261407	50		01	3750		
						1	299609	1	291675					
0261	326435	261245	326437	2563					50		ALL	3750		
0262	326437	261302	326437	0630					50		01	3300		
0263	326431	261218	326431	2520	1	298975	1	222289	50		01	3800	393870	
								1	295413	53	02	3800		
								1	391116	86				
								1	93158					
0264	326431	261218	326431	2520					50		01	3750	393870	
0265	326437	261245	326437	2563					50		01	3600		
0266	326431	261245	326431	2520	1	261218	1	22963	50		01	3600		
						1	299609	1	261245	77				
						1	391065	1	291675					
						1	92674	1	392235					
								1	93583					
								1	93722					
0267	326431	261218	326431	2520	1	298975	1	222289	50		01	3800	393870	
								1	297472	77				
								1	391116					
								1	392884					
								1	93158					
0268	326431	261218	326431	2520					50		01	2900	393870	
0269	326432	261407	326432	2561	1	261413	1	261407	50		01	3700		
						1	299609	1	291675					
0270	326431	261218	326431	2520	1	220197	1	222289	50		01	3800	393870	
								1	66538	86				
								1	93158					
0271	326437	261218	326437	2527	1	391065	1	391070	50		01	3600	393870	
								1	66538					
0272	326432	261407	326432	2561	1	261413	1	261407	50		01	3700		
						1	299609	1	291675					
0273	326437	261245	326437	2563				1	93879	50	01	3600		
0274	326437	261218	326437	2527	1	391065	1	391070	39		01	3600	393870	
									50					
									65					

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
0275	326437	261218	326437	2527			1	299361	50		01	3600	393870	
							1	93879	93					
0276	326437	261218	326437	2527	1	220197			50		01	3600	393870	
									93					
0277	326437	261245	326437	2563	1	220197	1	291630	50		01	3150		
							1	93879						
0278	326435	261245	326437	2563			1	93879	50		01	3750		
0279	326437	261245	326437	2563			1	392918	50		01	3800		
							1	93879	53					
0280	326431	261218	326431	2520	1	298975	1	222289	50		01	3800	393870	
							1	261322	86					
							1	391116						
							1	392150						
							1	93158						
							1	93879						
0281	326437	261218	326437	2527					50		01	2900	393870	
									93					
0282	326435	261218	326437	2527					50		01	2900	393870	
0283	326435	261218	326437	2527					50		01	3200	393870	
									65					
0284	326437	261218	326437	2527					50		01	3700	393870	
									53					
									65					
0285	326437	261245	326437	2563			1	93879	50		01	3800		
									93					
0286	326437	261223	326437	2527	1	261218	1	261223	50		01	3100		
					1	299609	1	291675						
							1	93879						
0287	326437	261245	326437	2563					50		01	3700		
0288	326437	261218	326437	2527					50		01	3600	393870	
0289	326431	261218	326431	2520					50		01	2900	393870	
0290	326431	261223	326431	2550					50		01	3000		
0291	326431	261245	326431	2550	1	211981	1	222669	50	0648	01	3750		
					1	222357	1	222670	65					
					1	22963	1	261245						
					1	261223	1	93843						
					1	91203								
					1	92674								
0292	326432	261407	326432	2561	1	261413	1	261407	50	0670	01	3750		
					1	299609	1	291675			02	3750		
0293	326431	261476	326431	2520	1	261218	1	261476	50	0647	01	3650		
					1	391062	1	291710	65					
					1	92674	1	93583						
0294	326431	261218	326431	2520					50		01	3600	393870	
0295	326432	261407	326432	2561	1	261413	1	261407	50	0691	01	3700		
					1	391062	1	291710			02	3700		
0296	326435	261245	326437	2563					50		01	3700		
0297	326432	261407	326432	2561	1	261413	1	261407	50		01	3700		
					1	299609	1	291675						
0298	326437	261218	326437	2527	1	391065	1	391070	50		01	3600	393870	
0299	326431	261218	326431	2520					50		01	3000	393870	
									88					
0300	326432	261407	326432	2561	1	261413	1	261407	50	0723	01	3700		
					1	391062	1	291710	78					
0301	326431	261218	326431	2520					50		01	3750	393870	

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
0302	326432	261407	326432	2561	1	261413	1	261407	50	0670	01	3700		
					1	299609	1	291675						
0303	326437	261245	326437	2563					50		01	3600		
0304	326435	261225	326437	2527	1	261218	1	261225	50		01	3400		
					1	299609	1	291675	93					
0305	326432	261413	326432	2561					50		01	3600		
0306	326437	261218	326437	2527					50		01	3600	393870	
									65					
									93					
0307	326435	261218	326437	2527					50		01	2900	393870	
0308	326432	261413	326432	2561	1	391065	1	393146	50		01	2900		
									65					
									84					
0309	326437	261218	326437	2527					50		01	2000	393870	
									77					
0310	326437	261223	326437	2527	1	261218	1	261223	50		01	2500		
					1	299609	1	291675	53					
					1	393800	1	392595	65					
0311	326437	261218	326437	2527					50		01	2900	393870	
									65					
									88					
0312	326432	261407	326432	2561	1	261413	1	261407	50		01	3600		
					1	299609	1	291675	65					
					1	92675	1	93583	77					
0313	326431	261218	326431	2520	1	391065	1	391070	50		01	3600	393870	
0314	326431	261219	326431	2520	1	261218	1	261219	50		01	2900		
					1	391062	1	291710						
0315	326437	261220	326437	2528	1	221851	1	261220	50		01	3600		
					1	22963	1	93583	65					
					1	261218								
					1	91203								
					1	92674								
0316	326437	261218	326437	2527					50		01	3200	393870	
									65					
									77					
									88					
0317	326437	261223	326437	2527	1	261218	1	261223	50		01	3600		
					1	391062	1	291710						
0318	326437	261223	326437	2527	1	261218	1	261223	50	0666	01	2900		
					1	299609	1	291675	93					
0319	326437	261225	326437	2527	1	261218	1	261225	39	0669	01	3300		
					1	391062	1	291710	50					
					1	393800	1	392595						
					1	91203	1	93583						
					1	92674								
0320	326437	261245	326437	2563	1	391062	1	291710	50		01	3700		
									93					
0321	326437	261543	326437	2527	1	261218	1	261543	50	0668	01	2900		
					1	391062	1	291710	88					
0322	326437	261225	326437	2527	1	261218	1	261225	39	0669	01	3300		
					1	391062	1	291710	50					
					1	393800	1	392595						
					1	91203	1	93583						
					1	92674								

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
0323	326437	261218	326437	2527					50		01	3600	393870	
0324	326437	261218	326437	2527					50		01	3750	393870	
									93					
0325	326437	261218	326437	2527					50		01	3750	393870	
0326	326437	261218	326437	2527	1	391065	1	391070	39		01	3600	393870	
					1	393474	1	392595	50					
									65					
0327	326432	261407	326432	2561	1	261413	1	261407	50		01	1900		
					1	299609	1	291675						
					1	92674	1	93585						
0328	326437	261222	326437	2527	1	261218	1	261222	39		01	3500		
					1	391065	1	391070	42					
									50					
									58					
									65					
0329	326431	261223	326431	2550					50		01	3750		
0330	326437	261218	326437	2528					50		01	3600	393870	
									88					
0331	326437	261218	326437	2527	1	391062	1	392590	50		01	3600		
									77					
0332	326437	261218	326437	2527	1	391065	1	391070	50		01	3600	393870	
					1	393474	1	392595						
									1	66538				
0333	326437	261218	326437	2528	1	221851	1	222283	50		01	3600	393870	
					1	22963	1	93583	65					
					1	91203								
					1	92674								
0334	326437	261245	326437	2563					50		01	3000		
									93					
0335	326432	261413	326432	2561					50		01	3750		
0336	326431	261218	326431	2520					50		01	2900	393870	
									88					
0337	326435	261223	326437	2527	1	261218	1	261223	50	0678	01	3400		
					1	299609	1	291675	53					
0338	326435	261245	326437	2563					50		01	3700		
									77					
0339	326431	261218	326431	2520					50		01	3750	393870	
0340	326437	261245	326437	2563					50		ALL	3750		
0341	326432	261413	326432	2561					50		01	3750		
									65					
									77					
0342	326432	261413	326432	2561					50		01	3600		
0343	326437	261223	326437	2527	1	261218	1	261223	39	0669	01	3300		
					1	391062	1	291710	50					
					1	393474	1	392595	53					
					1	91203	1	93583						
					1	92674								
0344	326431	261245	326431	2520	1	261218	1	261245	50		01	3600		
					1	299609	1	291675						
0345	326431	261245	326431	2520	1	261218	1	261245	50		01	2900		
					1	299609	1	291675						
0346	326431	261245	326431	2520	1	261218	1	261245	50	0722	01	3700		
					1	391062	1	291710						
0347	326437	261245	326437	2528	1	261218	1	261245	50		01	3000		
					1	299609	1	291675						
0348	326437	261245	326437	2563	1	391062	1	291710	50		01	3700		

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
0349	326437	261218	326437	2527	1	393474	1	392595	50		01	3600	393870	
0350	326437	261218	326437	2527	1	393474	1	392595	39 50 65		01	3600	393870	
0351	326437	261218	326437	2527					50 65 77 88		01	3200	393870	
0352	326432	261407	326432	2561	1	261413	1	261407	50		01	3700		
					1	391062	1	291710			02	3700		
0353	326437	261245	326437	2563	1	391062	1	291710	50	0687	01	3700		
0354	326431	261218	326431	2520					50 65 88		01	2900	393870	
0355	326437	261218	326437	2528					50		01	3750	393870	
0356	326431	261218	326431	2520					50		01	3750	393870	
0357	326431	261543	326431	2520	1	261218	1	261543	50	0656	01	2900		
0358	326437	261218	326437	2528					50 53 77 84		01	3650	393870	
0359	326437	261245	326437	2563			1	66538	50 93		01	3000		
0360	326437	261218	326437	2527					50 65		01	2650	393870	
0361	326431	261245	326431	2520	1	261218	1	261245	50	0650	01	3100		
					1	299609	1	291675						
0362	326431	261543	326431	2520	1	261218	1	261543	50	0717	01	2900		
					1	391062	1	392590						
0363	326437	261245	326437	2563	1	391062	1	291710	50		01	3700		
					1	92674	1	93583						
0364	326435	261218	326437	2527					50		01	2800	393870	
0365	326432	261407	326432	2561	1	261413	1	261407	50	0691	01	3700		
					1	391062	1	291710						
0366	326431	261245	326431	2520	1	261218	1	261245	50	0656	01	3700		
					1	299609	1	291675						
0367	326437	261245	326437	2563	1	391062	1	291710	50	0687	01	3700		
0368	326431	261543	326431	2520	1	261218	1	261543	50	0656	01	2900		
0369	326432	261407	326432	2561	1	261413	1	261407	50		01	3700		
					1	391062	1	291710						
					1	92674	1	93583						
0370	326437	261218	326437	2527					50		01	3750	393870	
0371	326437	261223	326437	2527	1	261218	1	261223	50	0371	01	3600		
					1	391062	1	291710						
0372	326437	261218	326437	2528					39 50		01	2900	393870	
0373	326432	261407	326432	2561	1	261413	1	261407	50 86	0670	01	3150		
0374	326435	261245	326437	2563					50		01	3050		
0375	326437	261245	326437	2563	1	291665	1	291710	50		01	3700		
0377	326437	261218	326437	2528					50		01	3600	393870	
0378	326437	261218	326437	2528					50		01	3750	393870	
0379	326437	261218	326437	2527	1	393800	1	392595	50		01	3600	393870	
							1	393537						
0380	326431	261218	326431	2520	1	293918	1	29693	50 53		01	3000	393870	

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
0381	326437	261218	326437	2527	1	22963			50 53 78 88		01	2900		
0382	326437	261218	326437	2527					50 53		01	3600	393870	
0383	326437	261245	326437	2563					50 93		01	3750		
0384	326431	261218	326431	2520					50		01	2900	393870	
0385	326431	261245	326431	2520	1	261218	1	261245	50		01	3750		
					1	299609	1	291675						
0386	326431	261218	326431	2520					42 50 78		01 02	3800 3800	393870	
0387	326436	261218	326437	2527					42 50 78		01	3800	393870	
0388	326437	261218	326437	2527					50 53 93		01	3600		
0389	326437	261218	326437	2528	1	393295	1	392595	50		01	3600	393870	
0390	326431	261218	326431	2520					50		01	3600	393870	
0391	326432	261407	326432	2561	1	261413	1	261407	50	0670	01	3150		
					1	299609	1	261675						
0392	326437	261218	326437	2527					50 78		01	3700	393870	
0393	326431	261218	326431	2520					50 78		01	2900	393870	
0394	326437	261245	326437	2563	1	291665	1	291710	50		01	3700		
0395	326431	261543	326431	2520	1	261218	1	261543	50	0395	01	3600		
					1	299609	1	291675	78					
0396	326431	261245	326431	2520	1	261218	1	261245	50	0396	01	3600		
					1	299609	1	291675	78					
0397	326431	261218	326431	2520					42 50 78		01	3600	393870	
0398	326431	261218	326431	2520					42 50		01	3800	393870	
0399	326437	261218	326437	2528					42 50 53		01	3600	393870	
0611	326431	261218	326431	2520					50				393870	
0630	326437	261302	STD.						50		01	3300		
0631	326436	261218	326437	2527					42 50 78 86		01	3800	393870	
0632	326431	261218	326431	2520					42 50 86		01 02	3800 3800	393870	
0633	326431	261245	326431	2520	1	261218	1	261245	50	0633	01	3700		
					1	391062	1	291710						
0634	326437	261245	326437	2563					50 93		01	3000		
0635	326432	261407	326432	2561	1	261413	1	261407	50	0635	01	3700		
					1	391062	1	291710			02	3700		

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
0636	326437	261223	326437	2527	1	261218	1	22963	50	0636	01	3200		
						1	299609	1	261223					
						1	92674	1	291675					
								1	93583					
0637	326431	261218	326431	2520					42		01	3800	393870	
									50					
									53					
									86					
0638	326437	261223	326437	2527	1	261218	1	260584	50	0638	01	3600		
						1	391062	1	261223					
						1	391065	1	291710					
								1	392235					
									84					
0640	326431	261218	326431	2520					42		01	3600	393870	
									50					
									78					
0641	326431	261218	326431	2520					42		01	3800	393870	
									50					
									78					
0642	326431	261218	326431	2520					42		01	3800	393870	
									50					
0643	326437	261218	326437	2528	1	393295	1	392595	50		01	3600	393870	
									86					
0644	326431	261218	326431	2520	1	391065	1	391070	50		01	3600	393870	
0645	326431	261218	326431	2520					50		01	3600	393870	
									86					
0646	326432	261413	326432	2561					50		01	3750		
									86					
0647	326431	261476	326431	2520	1	261218	1	261476	50	0647	01	3650		
						1	391062	1	291710					
						2	92674	2	93583					
0648	326431	261245	326431	2550	1	211981	1	211889	50	0648	01	3750		
						1	222357	1	221953					
						1	22963	1	222669					
						1	261223	1	22267					
						3	91203	1	261245					
						1	92674	3	93583					
								1	93843					
0649	326437	261218	326437	2528	1	221851	1	222283	50		01	3600	393870	
						1	22963	1	93583					
						2	91203							
						1	92674							
0650	326431	261245	326431	2520	1	261218	1	261245	50	0650	01	3100		
						1	299609	1	291675					
0651	326431	261218	326431	2520					50		All	2900	393870	
0652	326431	261218	326431	2520					42		01	3600	393870	
									50					
0653	326437	261218	326437	2527					42		01	3600	393870	
									50					
0654	326437	261245	326437	2563	1	291665	1	291710	50		01	3700		
0655	326431	261218	326431	2520					50		01	3000	393870	
0656	326431	261543	326431	2520	1	261218	1	261543	50	0656	All	2900		
						1	299609	1	291675					
0657	326431	261218	326431	2520					50		01	2900	393870	
0658	326437	261218	326437	2528					50		01	3750	393870	
0659	326431	261218	326431	2520					50		01	2900	393870	

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
0660	326437	261218	326437	2527					50		01	2650	393870	
0661	326437	261218	326437	2528					50		01	3000	393870	
0662	326431	261218	326431	2520					50		01	2900	393870	
									78					
0663	326437	261218	326437	2528					50		01	3750	393870	
0664	326431	261218	326431	2520					50		01	2900	393870	
0665	326437	261218	326437	2527					42		01	3600	393870	
									50					
0666	326437	261223	326437	2527	1	261218	1	261223	50	0666	01	2900		
					1	299609	1	291675						
0667	326437	261218	326437	2527					50		01	3450	393870	
											02	3450		
0668	326437	261543	326437	2527	1	261218	1	261543	50	0668	01	3750		
					1	391062	1	291710						
0669	326437	261223	326437	2527	1	261218	1	261223	39	0669	01	3300		
					1	391062	1	291710	50					
					1	393474	1	392595	53					
					1	91203	2	93583						
					1	92674								
0670	326432	261407	326432	2561	1	261413	1	261407	50	0670	01	3750		
					1	299609	1	291675						
0671	326437	261245	326437	2563					50		01	3750		
0672	326437	261218	326437	2528					50		01	3600	393870	
									53					
0673	326437	261218	326437	2527					50		01	2650	393870	
0674	326431	261245	326431	2520	1	261218	1	261245	50	0674	01	3600		
					1	299609	1	291675						
0675	326437	261543	326437	2528	1	261218	1	261543	50	0675	01	3750		
					1	299609	1	291675						
0676	326437	261245	326437	2563	1	291665	1	291710	50		01	3700		
0677	326431	261218	326431	2520					50		01	3600	393870	
									53					
0678	326431	261222	326431	2520	1	261218	1	261222	39	0678	01	3500		
					1	391065	1	391070	42					
									50					
									58					
									65					
0679	326437	261218	326437	2527	1	391062	1	392950	50		01	3600	393870	
									77					
0680	326437	261245	326437	2563	1	291665	1	291710	50		01	3750		
					2	92674	2	93583						
0682	326437	261682	326432	2561	1	261413	1	261682	50	0682	01	3600		
					1	391062	1	291710	93		02	3600		
0683	326431	261218	326431	2520					50		01	2800	393870	
0684	326435	261223	326437	2527	1	22963	1	261223	50	0684	01	3400		
					1	261218	1	291675	53					
					1	299609								
0685	326437	261218	326437	2528					50		01	3600	393870	
0686	326432	261407	326432	2561	1	261413	1	261407	50	0686	01	3150		
					1	299609	1	291675	53					
0687	326437	261245	326437	2563	1	291665	1	291710	50		01	3700		
0688	326437	261218	326437	2527					50		01	3750	393870	
0689	326431	261218	326431	2520					50		01	3750	393870	
0690	326431	261223	326431	2550					50		01	3750		

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block		
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes	
0691	326432	261407	326432	2561	1	261413	1	261407	50	0691	01	3700			
					1	391062	1	291710							
0692	326437	261245	326437	2563					50		01	3750			
									93						
0693	326437	261245	326437	2563					50		01	3100			
									93						
0694	326431	261245	326431	2520	1	261218	1	261245	50	0694	01	2900			
					1	291665	1	291710							
0695	326431	261218	326431	2520					50		01	3750	393870		
0696	326431	261245	326431	2520	1	261218	1	261245	50	0696	01	3100			
					1	291665	1	291710							
0697	326437	261218	326437	2528					39		01	2900	393870		
									50						
0698	326437	261245	326437	2563					50		01	3100			
									93						
0699	326437	261245	326437	2563					50		01	3150			
0700	326431	261218	326431	2520					50		01	2900	393870		
0701	326437	261218	326437	2527					50		01	2900	393870		
									93						
0702	326437	261245	326437	2563					50		01	3700			
									93						
0703	326437	261245	326437	2563					50		01	3700			
0704	326437	261218	326437	2527					53		01	2900	393870		
									78						
									88						
0705	326435	261218	326437	2527	1	391065	1	392235	42	705	01	2800	393870		
									50						
									53						
									65						
									77						
									93						
0706	326431	261223	326431	2550					50		01	3750			
0707	326437	261218	326437	2528					50		01	3650	393870		
									53						
									77						
									84						
0708	326435	261245	326437	2563	2	91203	9	93583	50		01	3800			
0709	326431	261543	326431	2550	1	261223	1	261543	50	0709	01	3600			
0710	326432	261413	326432	2561					50		01	2900			
0711	326437	261413	No Replacement Repair With Individual Parts.									01	2900		
0712	326437	261218	326437	2527					50		01	3700	393870		
									78						
0713	326432	261413	326432	2561	1	391062	1	392590	50		01	3600			
0714	326437	261245	326437	2563					50		01	3000			
0715	326437	261218	326437	2527					50		01	3600	393870		
0716	326437	261218	326437	2527					50		01	3600	393870		
									53						
0717	326431	261543	326431	2520	1	261218	1	261543	50	0717	01	2900			
					1	391062	1	291710							
0718	326437	261245	326437	2563	1	291665	1	291710	50		01	3700			
0719	326437	261407	No Replacement Repair With Individual Parts.									01	1800		
0720	326437	261944	No Replacement Repair With Individual Parts.									All	3700		
0721	326437	261223	326437	2527	1	261218	1	261223	50		01	2900			
					1	299609	1	291675							

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block		
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes	
0722	326431	261245	326431	2520	1	261218	1	261245	50	0722	01	3700			
					1	26828	1	291675	65						
					1	292260	1	65906	78						
					1	299609	1	68293							
0723	326432	261407	326432	2561	1	261413	1	261407	50	0723	01	3700			
					1	391062	1	291710	65						
0724	326435	261245	326437	2563	3	92674	3	93583	50		01	3600			
									65						
									77						
0725	326437	261218	326437	2527					50		01	3600	393870		
									65						
0726	326436	261407	No Replacement Repair With Individual Parts.									01	3150		
0727	326431	261218	326431	2520					50		01	3000	393870		
									88						
0728	326432	261413	326432	2561					50		01	3600			
0729	326437	261245	326437	2563	1	291665	1	291710	50		01	3750			
0730	326432	261407	326432	2561	1	261413	1	261407	50	0730	01	3750			
					1	291665	1	291710							
0731	326437	261218	326437	2527					50		01	3750	393870		
									65						
0732	326437	261407	No Replacement Repair With Individual Parts.									01	3150		
0733	326435	261245	326437	2563					50		01	3050			
0734	326431	261218	326431	2520					50		01	2900			
0735	326432	261407	326432	2561	1	261413	1	261047	50	0735	01	3150			
					1	391062	1	291665							
0736	326437	261245	326437	2563	1	291665	1	291710	50	0736	01	3700			
0737	326432	261407	326432	2561	1	261413	1	261407	50	0737	01	3150			
0738	326437	261218	326437	2527					50		01	3600	393870		
									93						
0739	326431	261223	326431	2550					50		01	3000			
0740	326437	261407	No Replacement Repair With Individual Parts.									01	3150		
0741	326437	261218	326437	2528					50		01	3600	393870		
0742	326437	261218	326437	2527	1	291665	1	291710	50		01	3700	393870		
0743	326431	261543	326431	2520	1	261218	1	261543	50	0743	01	3750			
					1	299609	1	291675							
0744	326432	261407	326432	2561	1	261413	1	261407	50	0744	01	3150			
					1	299609	1	291675	65						
									77						
									88						
0745	326432	261407	326432	2561	1	261413	1	261407	50	0745	All	3750			
					1	299609	1	291675							
0746	326437	261245	326437	2563	1	393800	1	393595	50		01	3750			
								1	394890	93					
0747	326431	261218	326431	2520					50		01	3750	393870		
0748	326437	261218	326437	2527					50		01	3750	393870		
0749	326437	261218	326437	2527					50		01	3500	393870		
0750	326432	261407	326432	2561	1	261413	1	261407	50	0750	01	3150			
					1	299609	1	291675	65						
									88						
0751	326437	261223	326437	2527	1	261218	1	261223	50	0751	01	3200			
					1	299609	1	291675	93						
0752	326437	261543	326437	2527	1	261218	1	261543		0752	01	2900			
					1	299607	1	291675							
0753	326437	261245	326437	2563					50		01	3000			
									93						

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block		
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes	
0754	326437	261245	326437	2563					50 93		01	3100			
0755	326432	261407	326432	2561	1	261413	1	261407	50	0755	01	3700			
					1	391062	1	291710	77						
0756	326431	261476	326431	2520	1	261218	1	261476	50	0756	01	3600			
					1	391062	1	291710							
0757	326431	261245	326431	2520	1	261218	1	261245	50	0757	01	3100			
					1	299609	1	291675							
0758	326437	261944	No Replacement Repair With Individual Parts.									All	3700		
0759	326432	261407	326432	2561	1	261413	1	261407	50	0759	01	3150			
					1	299609	1	291675	65						
									88						
0760	326437	261218	326437	2527					50		01	3750	393870		
									88						
0761	326437	261218	326437	2528					50		01	3600	393870		
0762	326431	261218	326431	2520					50		01	3750	393870		
0763	326431	261218	326431	2520					50		01	3800	393870		
0764	326437	261245	326437	2563	1	391062	1	291710	50		01	3750			
									88						
0765	326437	261543	326437	2527	1	261218	1	261543	50		01	2900			
					1	391062	1	291710							
0766	326431	261218	326431	2520					50		All	3800	393870		
0767	326436	261218	326437	2527					50		All	3800	393870		
0768	326435	261218	326437	2527					50		01	3200	393870		
0769	326432	261413	326432	2561					50		01	3200			
0770	326437	261218	326437	2528					42		01	3600	393870		
									50						
									77						
									84						
0771	326437	261245	326437	2563					50		01	3000			
0772	326437	261245	326437	2563	1	391062	1	291710	50		01	3750			
0773	326432	261413	326432	2561					50		01	3750			
0774	326437	261245	326437	2563	1	391062	1	291710	50		01	3700			
0775	326431	261218	326431	2520					50		01	3750	393870		
0776	326437	261245	326437	2563					50		01	3700			
0777	326437	261543	326437	2527	1	261218	1	261543	50		01	2900			
					1	391062	1	291710							
0778	326431	261543	326431	2520	1	261218	1	261543	50	0778	01	2900			
					1	391062	1	291710							
0779	326437	261543	326437	2527	1	261218	1	261543	50	0779	01	2900			
					1	391062	1	291710							
0780	326432	261407	326432	2561	1	261413	1	261407	50	0780	01	3150			
					1	299609	1	291675							
0781	326437	261413	No Replacement Repair With Individual Parts.									01	3750		
0782	326437	261245	326437	2563	1	391062	1	291710	50		01	3750			
0783	326437	261218	326437	2527					50		01	3600	393870		
									53						
0784	326437	261543	326437	2527	1	261218	1	261543	50	0784	01	3600			
					1	299609	1	291675							
0785	326432	261413	326432	2562					50		01	3750			
0786	326432	261407	326432	2561	1	261413	1	261407	50	0786	01	3150			
					1	391062	1	291710							
0787	326437	261245	326437	2563	1	391062	1	291710	50		01	3150			
0788	326437	261245	326437	2563	1	391062	1	291710	50		01	3150			

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block		
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes	
0789	326437	261543	326437	2527	1	261218	1	261543	50	0789	01	3600			
					1	391062	1	291710							
0790	326431	261543	326431	2520	1	261218	1	261543	50	0790	01	3600			
					1	391062	1	291710			02	3600			
0791	326431	261218	326431	2520					50		01	3000	393870		
									88						
0792	326431	261543	326431	2520	1	261218	1	261543	50	0792	01	3600			
					1	391062	1	291710							
0793	326431	261543	326431	2520	1	261218	1	261543	50	0793	01	3600			
					1	391062	1	291710			02	3600			
0794	326431	261543	326431	2520	1	261218	1	261543	50	0794	01	2900			
					1	391062	1	291675							
0795	326437	261543	326437	2527	1	261218	1	261543	50	0795	01	2900			
					1	391062	1	291710							
0796	326431	261543	326431	2520	1	261218	1	261543	50	0796					
					1	299609	1	291675							
0797	326437	261218	326437	2527					50		All	3450	393870		
0798	326431	261543	326431	2520	1	261218	1	261543	50	0798	01	2900			
					1	299609	1	291675							
0799	326431	261218	326431	2520					50		01	2900	393870		
0800	326437	261218	326437	2527					50		01	3750	393870		
0801	326431	261543	326431	2520	1	261218	1	261543	50	0801	01	3600			
					1	391062	1	291710							
0802	326431	261543	326431	2520	1	261218	1	261543	50	0802	All	3600			
					1	299609	1	291675							
0803	326431	261218	326431	2520					42		01	3800	393870		
									50						
									53						
0804	326431	261543	326432	2520	1	261218	1	261543	50		01	3600			
					1	391062	1	291710							
2520	326431	261218	STD.						50		01	3750	393870		
											02	3750			
											03	3750			
											04	3750			
											05	3750			
											06	3750			
2521	326431	261543	326431	2520	1	261218	1	261543	50	2521	01	2900			
					1	391062	1	291710			02	2900			
											03	3750			
											04	3600			
											05	2900			
											06	2900			
											07	3600			
											08	3600			
											09	2900			
2522	326431	261245	326431	2520	1	261218	1	261245	50	2522	All	3700			
					1	299609	1	291675							
2527	326437	261218	STD.						50		All	3750	393870		
2528	326437	261218	STD.						50		All	3750	393870		
2529	326437	261413	No Replacement Repair With Individual Parts.									01	3750		
											02	3750			
2530	326431	261543	326431	2520	1	261218	1	261543	50	2530	01	3600			
					1	391062	1	291710							
2550	326431	261223	STD.						50		All	3750			
2560	326432	262682	326432	2561	1	261413	1	261682	50	2560	All	2900			
					1	391062	1	291710							

326400 to 326499

Original Engine			Make From		Remove		Add		Note	Change to Type	Trim	RPM	Short Block	
Type	Model	Crank	Model	Type #	Qty	Part #	Qty	Part #					Part #	Notes
2561	326432	261413	STD.						50		01	3750		
											02	3750		
2562	326432	261407	326432	2561	1	261413	1	261407	50	2562	01	3750		
					1	299609	1	291675			02	3750		
2563	326437	261245	STD.						50		All	3700		
2580	326431	261218	326431	2520					42		01	3600	393870	
									50					
									78					
2581	326431	261218	STD.						50		01	3600	393870	
2582	326431	261220	STD.						50		01	3750		
2583	326431	261218	326431	2520					50		01	3800	393870	
									53					
									88					